

<b>GENSET</b>	<b>Model</b>	<b>RHD 12000 TE</b>
	<b>Output Power (VA)</b>	12000
	<b>Output Voltage</b>	230/400
	<b>Frequency (Hz)</b>	50 Hz. / 3000 rpm.
	<b>Overload Protection</b>	With Thermal Circuit Breaker
<b>ENGINE</b>	<b>Engine Model</b>	HONDA GX 620
	<b>Engine Type</b>	4 STROKE, OVERHEAD VALVE, SINGLE CYLINDER, AIR COOLED
	<b>No of Cylinder</b>	Single Cylinder
	<b>Displacement</b>	614
	<b>Engine Power @ 3000 rpm</b>	20 Hp
	<b>Cooling System</b>	Air Cooled
	<b>Ignition System</b>	Transistored Magneto
	<b>Sump Oil Capacity / lt</b>	1,9
	<b>Fuel Capacity / lt</b>	16
	<b>Starting Sytem</b>	ELECTRICAL
	<b>Oil Protection and Alert System</b>	Low Oil Level Protection and Lighting Alert
<b>ALTERNATOR</b>	<b>Alternator Make</b>	SACCARDO – ITALIAN
	<b>Generator Type</b>	Synchronous Type, Single Bearing
	<b>Output Power (kWe)</b>	7,5
	<b>Voltage Reulation</b>	Electronic AVR
	<b>Output Voltage (V)</b>	230
	<b>Frequency (Hz)</b>	50 Hz. / 3000 rpm.
	<b>No of Phase</b>	Single Phase
	<b>Power Factor</b>	Cos fi 0,8
<b>DIMENSION</b>	<b>Box Dimensions LxWxH mm</b>	920x580x610
	<b>Dry Weight (Kg)</b>	150
	<b>Noise Level (dBA @ 7 meter)</b>	93



**GUCEVI JENERATOR SAN. VE TIC. LTD. STI.**

**Headquarter :**

Address : Dumlupinar mahallesi Volkangul sokak No.12 D.2 Fikirtepe İstanbul - TURKEY

Tel No : +90 216 565 2658 Faks No. : +90 216 565 4640

[www.thepwrhouse.net](http://www.thepwrhouse.net)