

GENSET	Model	RHD 5500 MR
	Output Power (W)	5500
	Output Voltage	230
	Frequency (Hz)	50 Hz. / 3000 rpm.
	Overload Protection	With Thermal Circuit Breaker
ENGINE	Engine Model	HONDA GX 390
	Engine Type	4 STROKE, OVERHEAD VALVE, SINGLE CYLINDER, AIR COOLED
	No of Cylinder	Single Cylinder
	Displacement	389
	Engine Power @ 3000 rpm	13 Hp
	Cooling System	Air Cooled
	Ignition System	Transistored Magneto
	Sump Oil Capacity / lt	1,1
	Fuel Capacity / lt	16
	Starting Sytem	RECOIL
	Oil Protection and Alert System	Low Oil Level Protection and Lighting Alert
ALTERNATOR	Alternator Make	SACCARDO – ITALIAN
	Generator Type	Synchronous Type, Single Bearing
	Output Power (kWe)	5,5
	Voltage Reulation	Electronic AVR
	Output Voltage (V)	230
	Frequency (Hz)	50 Hz. / 3000 rpm.
	No of Phase	Single Phase
	Power Factor	Cos fi 1
DIMENSION	Box Dimensions LxWxH mm	820x580x610
	Dry Weight (Kg)	80
	Noise Level (dBA @ 7 meter)	71



GUCEVI JENERATOR SAN. VE TIC. LTD. STI.

Headquarter :

Address : Dumlupınar mahallesi Volkangul sokak No.12 D.2 Fikirtepe İstanbul - TURKEY

Tel No : +90 216 565 2658 Faks No. : +90 216 565 4640

www.thepwrhouse.net